

South Carolina Net Call-Up Procedures

4G1B, 4G1B THIS IS NNN0__ SECTION 1 STATIONS OVER

(note: the dual 4G1B only used on the first call)

4G1B THIS IS NNN0__ SECTION 2 STATIONS OVER

4G1B THIS IS NNN0__ SECTION 3 STATIONS OVER

4G1B THIS IS NNN0__ SECTION 4 STATIONS OVER

4G1B THIS IS NNN0__ SECTION 5 STATIONS OVER

4G1B THIS IS NNN0__ SECTION 6 STATIONS OVER

Acknowledge all stations: Call for additional stations

4G1B THIS IS NNN0__ OVER

Assign alternate and ask for them to call for stations

NNN0__ ASSUME ALTERNATE NET CONTROL , CALL FOR ADDITIONAL STATIONS OVER

Alternate answers

THIS IS NNN0__ ROGER OUT followed by

4G1B THIS IS NNN0__ OVER

Acknowledge additional stations and pass them or no stations heard to net control

NNN0__ THIS IS NNN0__ CHECK IN NNN0XXX, NNN0YYY or NO STATIONS HEARD OVER.

Abbreviated call signs:

4G1B THIS IS NNN0__ ABBREVIATED CALL SIGNS ARE AUTHORIZED OUT.

Pass all traffic in precedence order.

AAA THIS IS NNN0__ CALL BBB AND PASS ONE ROUTINE OUT

aaa calls bbb

BBB THIS IS AAA ONE ROUTINE OVER

bbb responds THIS IS BBB ROGER OVER

When all traffic has been passed, get remarks from staff members followed by member remarks in check in order. Between remarks as needed make additional net calls:

4G1B THIS IS NNN0__ OVER

When all business has been conducted you may authorize at your discretion a free net.:

4G1B THIS IS NNN0__ USE FULL CALL SIGNS THE NET IS IN FREE STATUS.

****STATIONS WISHING TO CLOSE DOWN MAY DO SO WITHOUT NOTIFYING NET CONTROL.**

When ready go back to a directed net and pass your net report to GBS3 or the station guarding for him. Return to a free net or close down.

Closing the net:

4G1B THIS IS NNN0__ CLOSE DOWN OUT.

As no transmissions are allowed after close down, if there are members using the frequency, as NCS you might wait to close down.

**** This is optional, but recommended, and may be included at the discretion of the net control station.**